



HC5 Universal Hand-held Controller

Operating Instructions

Point the handset at the detector and press a button. The beam angle is quite narrow, so accurate aiming is important.

Key Assignment

- 1 - Scene 1, short press to recall, long press to set.
- 2 - Scene 2, short press to recall, long press to set.
- 3 - Scene 3, short press to recall, long press to set.
- 4 - Scene 4, short press to recall, long press to set.
- 5 - Scene 5, short press to recall, long press to set.
- 6 - Scene 6, short press to recall, long press to set.
- 7 - Short press to turn off light/s associated with an individual sensor; long press to dim light/s associated with an individual sensor.
- 8 - Short press to turn on light/s associated with an individual sensor; long press to brighten light/s associated with an individual sensor.
- 9 - Short press to turn off group of lights; long press to dim group.
- 10 - Short press to turn on group of lights; long press to brighten group.

Product Compatibility

Please note that many products respond only to keys 7 and 8 for individual dimming and/or turning on and off.

Technical Data

Dimensions: 120 x 56 x 22mm

Weight: 115g

Battery type: Alkaline AAA x 2

Typical battery life: 1 year

Operating range: 2.5m when used with standard Ex-Or detectors and up to 16m when used with Hi-Bay types ('HB' suffix in the part number)

Ex-Or

Haydock Lane, Haydock, Merseyside WA11 9UJ

Telephone: + 44 (0)1942 719229

Fax: + 44 (0)1942 272767

Email: technicalsales.ex-or@honeywell.com



W4127D

