

HC5A Universal Hand-held Controller



Operating Instructions

Point the handset at the detector and press a button. The beam angle is quite narrow, so accurate aiming is important.

Key Assignment

- S1 - Scene 1, short press to recall, long press to set.
- S2 - Scene 2, short press to recall, long press to set.
- S3 - Scene 3, short press to recall, long press to set.
- S4 - Scene 4, short press to recall, long press to set.
- S5 - Scene 5, short press to recall, long press to set.
- S6 - Scene 6, short press to recall, long press to set.
- - Short press to turn off light/s associated with an individual sensor; long press to dim light/s associated with an individual sensor.
- + - Short press to turn on light/s associated with an individual sensor; long press to brighten light/s associated with an individual sensor.
- - Short press to turn off group of lights; long press to dim group.
- + - Short press to turn on group of lights; long press to brighten group.

Product Compatibility

Please note that many products respond only to keys  and  for individual dimming and/or turning on and off.

Technical Data

Dimensions: 135mm (h) x 44mm (w) x 6mm (d)

Weight: 45g approx

Battery type: 3V DC CR2032 Lithium Button Cell

Expected battery life: 3 year

Operating range: 2.5m when used with standard detectors and up to 12m when used with Mid-Bay types or 16m when used with Hi-Bay types.



W5104C