


Electromechanical time switches

Electromechanical time switches with trippers with daily or weekly programming and charge reserve, designed for household use.

NAPA

- Selector switch with 3 positions to set the operating mode Accessory for wall or DIN rail mounting
- External quadrant with captive trippers 3
- Internal quadrant fitted with the dials to indicate the current 4 time





NAPA-RD Napa-RW

DIMENSIONS (mm)











DAILY / WEEKLY TIME SWITCHES

- 3-positions selector switch for the operating mode: **0** off permanently
 - I on permanently
 - () automatic operation by trippers
- Models for wall, rear-panel or DIN rail mounting





2

• Wall mounting, rear-panel or DIN rail

Code	Model	Description	Quadrant	N° trippers
VE049300	NAPA-ED	Daily without charge reserve	24 hours	96
VP884100	NAPA-D	Daily with charge reserve	24 hours	96
VP885800	NAPA-W	Weekly with charge reserve	7 days	84
Rear-panel mounting)			

Code	Model	Description	Quadrant	N° trippers
VP886600	NAPA-RD	Daily with charge reserve	24 hours	96
VP887400	NAPA-RW	Weekly with charge reserve	7 days	84



TECHNICAL INFORMATION

GENERAL CHARACTERISTICS

Power supply	V AC	230 (-15% ÷ +10%)	
Frequency	Hz	50 / 60	
Absorption	VA	1.8	
Output		change-over contact	
		16 (4) A / 250 V	
Charge reserve (not available for	100 h after a charge		
		uninterrupted for 48 h	
Operating accuracy	S	±1 per day	
		non-accumulating	
Fastened	Model ED / D / W	wall / rear-panel / DIN	
	Model RD / RW	rear-panel	
Minimum intervention time	Model ED / D / RD	15 min	
	Model W / RW	2 hours	
Operating temperature	°	-10 ÷ +45	
Degree of protection	IP	20	

REFERENCE STANDARDS

Conformity with Community Directives: 2014/35 / EU (LVD) and 2014/30 / EU (EMCD) is declared with reference to the following standards: • EN 60730-2-7

Energy Conservation Solutions Pty Ltd


Exclusive Distributor for VEMER in Australia Locations: VIC/TAS, NSW, QLD, ACT, SA/NT & WA Phone: 1300 306 136 For contact details visit: www.ecs.net.au




CONNECTION DIAGRAM









TIME MANAGEMENT

CONNECTABLE LOADS

Incandescent	P	3000 W
Fluorescent		1200 VA
Low voltage halogen	\square	2000 VA
Halogen (230 V~)	¢ (+++) ¢	3000 W
Low consumption lamp (CFL)		1000 VA
Low consumption lamp (CFL)	-	900 VA
Led	Д	200 VA